

CERTIFICATE of Conformity



Registration No.: A3 50716312 0001

Report No.: CN25LI3C 001

Holder: MEAN WELL Enterprises Co., Ltd.
No. 28, Wuquan 3rd Rd.,
Wugu District,
New Taipei City 24891
Taiwan

Product: Power Conversion Equipment
(AC DC Bidirectional Power Supply)

Identification: Type Designation:
BIC-5K-24, BIC-5K-48, BIC-5K-96, BIC-5K-380,
BIC-5K-24MOD, BIC-5K-48MOD, BIC-5K-96MOD, BIC-5K-380MOD
Firmware version: R010
Remark : Refer to test report CN25LI3C 001 for detail.

Tested acc. to: EN 50549-1:2019+A1
EN 50549-10:2022

The certificate of conformity refers to the above mentioned product. This is to certify that the specimen is in conformity with the assessment requirement mentioned above. This certificate does not imply assessment of the production of the product and does not permit the use of a TÜV Rheinland mark of conformity.

Date 13.02.2026

Durch die DAKKS nach
DIN EN ISO/IEC 17065:2013

akkreditierte Zertifizierungsstelle.
Die Akkreditierung gilt nur für den in der
Urkundenanlage D-ZE-14169-01-02
aufgeführten Akkreditierungsumfang.

Certification Body

Dean Cao

TÜV Rheinland LGA Products GmbH - Tillystraße 2 - 90431 Nürnberg

Certificate No.: A3 50716312 0001

Certificate Of Conformity

License holder: MEAN WELL Enterprises Co., Ltd.
No. 28, Wuquan 3rd Rd., 248 Wugu Dist., New Taipei City, Taiwan

Type of product: Power Conversion Equipment
(AC DC Bidirectional Power Supply)

Model: BIC-5K-24, BIC-5K-48, BIC-5K-96, BIC-5K-380, BIC-5K-24MOD,
BIC-5K-48MOD, BIC-5K-96MOD, BIC-5K-380MOD

Firmware version: R010

Standard: **EN 50549-1:2019+A1**
Requirements for generating plants to be connected in parallel with distribution networks - Part 1: Connection to a LV distribution network -Generating plants up to and including Type B
EN 50549-10:2022
Requirements for generating plants to be connected in parallel with distribution networks - Part 10: Tests for conformity assessment of generating units

Report No.: CN25LI3C 001

Date of issue: 13.02.2026

Remark: In case of voltage below 95% Un (220 Vac), the apparent power of power unit will reduce to maintain the current limit. To reach full power on plant level, the permanent power derating or redundant amount of units could be implemented.

The verification of conformity refers to the above mentioned product. This is to verify that the specimen is in conformity with the assessment requirement mentioned above. This verification does not imply assessment of the production of the product and does not permit the use of a TÜV Rheinland mark of conformity.



Dean Cao

Certifier

EN 50549-1:2019+A1 Annex C Parameter Table

Clause(s) / sub-clause(s) of EN 50549-1:2019+A1	Parameter ^a	Remarks / additional information ^b	Typical value range	Value default	
4.4.2 Operating frequency range	47,0 – 47,5 Hz Duration	Unlimited	0 – 20 s	0 s	
	47,5 – 48,5 Hz Duration	Unlimited	30 – 90 min	30 min	
	48,5 – 49,0 Hz Duration	Unlimited	30 – 90 min	30 min	
	49,0 -51,0 Hz Duration	Unlimited	not configurable	unlimited	
	51,0 – 51,5 Hz Duration	Unlimited	30 – 90 min	30 min	
	51, 5 – 52 Hz Duration	Unlimited	0 – 15 min	0 s	
4.4.3 Minimal requirement for active power delivery at underfrequency	Reduction threshold	Not configurable	49 Hz – 49,5 Hz	49,5 Hz	
	Maximum reduction rate	No reduction (≤ 2% P _M / Hz)	2– 10 % PM/Hz	≤ 10% P _M / Hz	
4.4.4 Continuous operating voltage range	Upper limit	110% U _n	not configurable	110% U _n	
	Lower limit	85% U _n	not configurable	85% U _n	
4.5.2 Rate of change of frequency (ROCOF) immunity	ROCOF withstand capability (defined with a sliding measurement window of 500 ms)	Up to ± 3.5 Hz/s	not defined	± 2 Hz/s	
4.5.3.2 Generating plant with non-synchronous generating technology	Maximum power resumption time	Not configurable	not defined	1 s	
	Voltage-Time-Diagram	Configurable (Most stringent requirement)	see Figure 6	Time [s]	U [p.u.]
				0,0	0,2
				0,15	0,2
				1,5	0,85
4.5.4 Over-voltage ride through (OVRT)	Maximum power resumption time	Not configurable	Not configurable	1 s	
	Voltage-Time-Diagram	Configurable (Default requirement)	not configurable	Time [s]	U [p.u.]
				0,0	1,25
				0,1	1,25
				0,1	1,20
				5,0	1,20
				5,0	1,15
				60	1,15
60	1,10				

Clause(s) / sub-clause(s) of EN 50549-1:2019+A1	Parameter ^a	Remarks / additional information ^b	Typical value range	Value default
4.5.5 Phase jump immunity	Phase jump immunity	Not configurable (Up to $\pm 180^\circ$)	Not configurable	$\pm 50^\circ$
4.6.1 Power response to over frequency	Threshold frequency f_1	Configurable	50,2 Hz – 52 Hz	50,2 Hz
	Droop	Configurable	2% – 12%	5%
	Power reference	Not configurable (P_{max})	P_M P_{max}	P_{max} , for synchronous generating technology and EESS P_M for other non-synchronous generating technology
	Intentional delay	Configurable	0 – 2 s	0 s
	Deactivation threshold f_{stop}	Configurable	50,0 Hz – f_1	deactivated
	Deactivation time t_{stop}	Configurable	0 – 600 s	--
	Acceptance of staged disconnection	Not configurable	yes no	yes
4.6.2 Power response to underfrequency	Threshold frequency f_1	Configurable	49,8 Hz – 46 Hz	49,8 Hz
	Droop	Configurable	2% – 12%	5%
	Power reference	Not configurable (P_{max})	P_M P_{max}	P_{max}
	Intentional delay	Configurable	0 – 2 s	0 s
4.7.2.2 Capabilities	Active factor / Reactive power (% P_D) range overexcited	0,9 – 1 / 43.6% P_n – 0	0,9 – 1 / 48.4% P_D – 0	0,9 – 1 / 43.6% P_n – 0
	Active factor / Reactive power (% P_D) range underexcited	0,9 – 1 / -43.6% P_n – 0	0,9 – 1 / -48.4% P_D – 0	0,9 – 1 / -43.6% P_n – 0
4.7.2.3 Control modes	Enabled control mode	Configurable Q setp. Q(U) Q(P) cos φ setp. cos φ (P)	Q setp. Q(U) cos φ setp. cos φ (P)	Q setpoint
4.7.2.3.2 Setpoint control modes	Q setpoint and excitation	Configurable	0 – 48.4% P_D	0
	Cos φ set point and excitation (ov and uv)	Configurable	1 – 0,9	1
	Time constant (τ)	Configurable (3 – 60 s)	3 s – 60 s	3,33 s

Clause(s) / sub-clause(s) of EN 50549-1:2019+A1	Parameter ^a	Remarks / additional information ^b	Typical value range	Value default
4.7.2.3.3 Voltage related control modes	Characteristic curve	Configurable Q(U)	D _{bchar} : -6% to +6 % U _n Q _{max char} : 10% – 100% of Q _{max over} and Q _{max under} Slope of the steepest: 1% – 100% Q _{max} / 1% U _n	indicate default characteristic (Figure 33 of EN 50549-10)
	Time constant (τ)	Configurable (3 s – 60 s)	3 s – 60 s	3,33 s
	Min cos φ	Configurable	0,0 – 1	0,4
	Lock in power	Configurable	0% – 20% P _n	deactivated
	Lock out power	Configurable	0% – 20% P _n	deactivated
4.7.2.3.4 Power related control mode	Characteristic curve	Configurable Cos φ (P) Q(P)	Q _{max char} : 10% – 100% of Q _{max over} and Q _{max under} Slope of the steepest: 2% – 200% Q _{max} / 10% P _n	indicate default characteristic (Figure 36 of EN 50549-10)
	Time constant (τ)	Configurable	3 s – 60 s	3,33 s
	Lock-in voltage	Configurable	100% U _n – 110% U _n	deactivated
	Lock-out voltage	Configurable	90% U _n – 100% U _n	deactivated
4.7.4.2.2 Zero current mode for converter connected generating technology	Enabling	Configurable	enable disable	disabled
	Static voltage range overvoltage	Configurable	100% U _n – 120% U _n	120% U _n
	Static voltage range undervoltage	Configurable	20% U _n – 100% U _n	50% U _n
4.9.2 Requirements on voltage and frequency protection	Threshold for protection as dedicated device [in A or kW, kVA]	Configurable	16 A – 250 kVA	--
	Undervoltage threshold stage 1	Configurable	0,2 U _n – 1 U _n	--
	Undervoltage operate time stage 1	Configurable	0,1 s – 100 s	--
	Undervoltage threshold stage 2	Configurable	0,2 U _n – 1 U _n	--
	Undervoltage operate time stage 2	Configurable	0,1 s – 5 s	--

Clause(s) / sub-clause(s) of EN 50549-1:2019+A1	Parameter ^a	Remarks / additional information ^b	Typical value range	Value default
	Overvoltage threshold stage 1	Configurable	1,0 U _n – 1,2 U _n	--
	Overvoltage operate time stage 1	Configurable	0,1 s – 100 s	--
	Overvoltage threshold stage 2	Configurable	1,0 U _n – 1,3 U _n	--
	Overvoltage operate time stage 2	Configurable	0,1 s – 5 s	--
	Overvoltage threshold 10 min mean protection	Configurable	1,0 U _n – 1,15 U _n	--
	Underfrequency threshold stage 1	Configurable	47,0 Hz– 50,0 Hz	--
	Underfrequency operate time stage 1	Configurable	0,1 s – 100 s	--
	Underfrequency threshold stage 2	Configurable	47,0 Hz – 50,0 Hz	--
	Underfrequency operate time stage 2	Configurable	0,1 s – 5 s	--
	Overfrequency threshold stage 1	Configurable	50,0 Hz – 52,0 Hz	--
	Overfrequency operate time stage 1	Configurable	0,1 s – 100 s	--
	Overfrequency threshold stage 2	Configurable	50,0 Hz – 52,0 Hz	--
	Overfrequency operate time stage 2	Configurable	0,1 s – 5 s	--
	4.10.2 Automatic reconnection after tripping	Lower frequency	Configurable	47,0 Hz – 50,0 Hz
Upper frequency		Configurable	50,0 Hz – 52,0 Hz	50,2 Hz
Lower voltage		Configurable	50% U _n – 100% U _n	85% U _n
Upper voltage		Configurable	100% U _n – 120% U _n	110% U _n
Observation time		Configurable	10 s – 600 s	60 s
Active power increase gradient		Configurable	6% – 3000% / min	10% / min
4.10.3 Starting to generate electrical power	Lower frequency	Configurable	47,0 Hz – 50,0 Hz	49,5 Hz
	Upper frequency	Configurable	50,0 Hz – 52,0 Hz	50,1 Hz
	Lower voltage	Configurable	50% U _n – 100% U _n	85% U _n

Clause(s) / sub-clause(s) of EN 50549-1:2019+A1	Parameter ^a	Remarks / additional information ^b	Typical value range	Value default
	Upper voltage	Configurable	100% U _n – 120% U _n	110% U _n
	Observation time	Configurable	10 s – 600 s	60 s
	Active power increase gradient	Configurable	6% – 3000% / min	10% / min
4.11.1 Ceasing active power	Remote operation of the logic interface	Configurable (Digital input by CANBUS/ MODBUS port)	yes no	No
4.11.2 Reduction of active power on set point	Remote operation NOTE: If yes further definition is provided by the DSO	Configurable (Digital input by CANBUS/ MODBUS port)	yes no	No
4.12 Remote information exchange	Remote information exchange required NOTE: If yes further definition is provided by the DSO	Configurable (The protocols will be agreed between the local DSO and PGUs at final installation)	yes no	No

Supplementary:

ov: Over-excited; uv: Under-excited

^a If additional parameters have been evaluated during the test, these shall be added as additional lines in the table.

^b This column should be used for manufacturer specific parameter descriptions.